



# AcquaTempus

arelia



## PROGRAMMING INSTRUCTIONS

With the following commands, you will be able to program your Acqua Tempus shower economizer to achieve maximum savings in water and energy

**To enter programming mode: press the INFO button for more than three seconds**

1

The screen lights up in GREEN to show Shower Time; (by default, all Acqua Tempus times are factory programmed at 5 minutes). With the screen in green colour, use the + and - buttons to adjust the shower time required for every shower

2

Press INFO again for 1 second and release, and the screen lights up in BLUE. This shows Soaping Time. Use the + and - buttons to adjust soaping time

3

Press INFO again for 1 second and release, the screen lights up RED. This shows Waiting Time. Use the + and - buttons to adjust waiting time

4

Press INFO again and the word OPE (OPEN) appears; this is the state in which the internal valve will remain after a shower has been taken and the waiting time has passed. If the - button is pressed CLO (CLOSED) will appear. In this case, at the end of the shower, the valve will close and for the next shower, the INFO (@) button needs to be pressed to open the valve. Normally, it is left at OPE

5

Press the INFO button again and a 3-digit number appears; This is a read-only parameter showing the charge of the battery. A healthy battery charge level will be around 3:80

6

Press the INFO button again and another figure appears showing the number of showers taken since installation. It is a read-only parameter

7

Press the INFO button again and a 3-digit figure shows. If the tap is opened the voltage generated by the turbine is shown. This is a read-only parameter to check the correct operation of the turbine

Afterwards, Acqua Tempus will turn off and be ready for use in the shower

## OTHER COMMANDS OF INTEREST

**MODE + INFO:** resets the timer; If the Acqua Tempus is unresponsive, pressing these two buttons will turn the Acqua Tempus off and on again, solving the problem

**SET + INFO:** shows the program version and simultaneously restores the factory settings

**OPEN TAPS DETECTOR:** After the Waiting Time, Acqua Tempus will automatically return to Shower Mode with the valve open for the next shower. If the tap has been left open water will start to come out uncontrollably. The Acqua Tempus has an open tap detector and will self-close, leaving it blocked. For the next user who wants to take a shower, they must press the INFO button (@) to reactivate the shower